

Optical Smoke Alarm

9V Battery Powered



Model Ei605CRF

Optical sensor chamber
9V Alkaline battery powered
RadioLINK wireless interconnection
Aesthetically pleasing, compact design
Large, easy to use Test button
Easy to fit twist-on base
Tested by VdS to EN14604:2005
5 year Guarantee



Product Description

The Ei605CRF is a RadioLINK Optical Smoke Alarm, powered by a 9V PP3 Alkaline battery (supplied)

The alarm gives a fire warning when adequate smoke enters the alarm

The alarm will interconnect wirelessly to other RadioLINK alarms in the property when activated

Up to 12 alarms can be interconnected on one system

RadioLINK enabled Smoke and/or Heat alarms can be "House Coded" together to prevent cross communication with other nearby RadioLINK systems

Operation

The red indicating light will flash once every 40 seconds to show that the alarm has performed an automatic self test

The red indicator will flash rapidly to show an alarm condition on the alarm that has triggered

The "Test/Hush" button will either silence false alarms (if briefly pressed) or to perform a self test (if pressed and held)

In "Test" mode the alarm will perform a self test and emit a full alarm sound

In "Hush" mode the alarm enters a ten-minute period of reduced sensitivity to overcome false alarm conditions. It will then automatically reset

When RadioLINK interconnected to other smoke/heat alarms, if one alarm is triggered, it will trigger all other interconnected alarms (only the triggered alarm will flash the red indicator)

The alarm will emit a beep every 40 seconds to indicate that the battery is depleted and needs replacing



Shannon Free Zone, Shannon, Co. Clare, Ireland.
Ph.+353 61 471277 Fx.+353 61 471053
Email. eielectronics@eiltd.ie
Web: www.eielectronics.com



Made in
Ireland

Technical Specification

1. The Smoke Alarm carries the VdS mark to indicate type testing to BS EN14604: 2005. It will meet the requirements of Grade F as defined in BS 5839: Pt.6: 2013. It carries the CE mark to indicate conformance to Low Voltage and Electromagnetic Compatibility Directives.
2. Optical (photoelectric) sensor with chamber and large high sensitivity photodiode. Insect resistant fine mesh screen with holes less than 0.030 inches.
3. The Alarm is powered by a 9V PP3 Alkaline battery (supplied). The unit is activated when the battery is connected to the snap fit connections. The battery should be replaced every 12 months, or when the unit starts to beep every 40 seconds along with a red indicator light.
4. Radio frequency: 868 MHz band in accordance with R&TTE Directive 1999/5/EC – this band has been designated for use with security products and only allows a 1% duty cycle, so continuous transmission and interference from external sources is extremely remote, and would be illegal.
5. Range: the type of building will be the major limiting factor e.g. the number and type of walls/ceilings that the radio signal has to pass through. As a guide, 30m should be the maximum distance between any of the alarms in the system.
6. Up to 12 units can communicate on one system – the range may be a limiting factor.
7. Low battery warning signal, beeps every 40 seconds for 30 days to indicate when replacement of the alarm is required.
8. Built in sounder giving a minimum sound output of 85dB (A) at 3m. The sounders contacts are soldered directly on to the piezo disc for additional security.
9. Manual integral Test/Hush button tests circuitry, sensor and horn and activates all interconnected alarms in the system. Also operates 'Hush' feature to silence nuisance alarms. Red LED on alarm cover will flash every 10 seconds to indicate that alarm is in 'Hush' mode and will automatically reset after approximately 10 minutes.
10. Automatic Self-Test: Optical sensor is tested every 40 seconds and unit beeps if a fault is detected.
11. External alarm RF signal: turns on sounder (without red LED flash) until it receives an 'Alarm Cancel' RF signal. Receiver remains on for an additional 11 seconds to check for further alarm signals. This ensures integrity of the interconnect function.
12. Units are in factory code when received (they will all communicate with each other). They must be "House Coded" to eliminate the risk of adjacent properties communicating with each other. After House Coding they will only communicate with other units coded at the same time.
13. House Code: operate the "House Code" button on the under side of the alarm, then place and twist alarm on to the base plate. Repeat this with all alarms in the system. A blue LED will flash through the front cover. Each alarm will "Learn" the serial numbers of all units in the system. The units will return to normal stand by mode after 30 minutes. Separate zones can be created within blocks of flats and other large buildings. These zones will not communicate with other "House Coded" zones in the same building, eliminating problems of nuisance alarm affecting all dwellings. If interconnection is required between dwellings, the need to cross boundaries with mains/interconnect cables is eliminated.
14. Repeater function: where distance or obstructions cause range restrictions, the Ei605WRF has a built-in multi-level repeater. On receiving an RF signal from another alarm, the unit will automatically re-transmit the signal to other alarms in the system. This provides multiple signal paths to give a strong and robust signal.
15. The Ei605CRF can be used with the Ei450, Ei411H and Ei412 RadioLINK Remote Control Switches to allow remote Test, Silence and Locate features. An Ei407 RadioLINK Manual Call Point is also available. See separate specification sheets for details.
16. Ambient Temperature Range: 4°C to 40°C. Humidity Range: 0 to 90 % relative humidity.
17. Dimensions: 115 x45mm. Weight inclusive of packaging: 200g.
18. 5 year guarantee.
19. Manufactured in Ireland.